

Product Highlights

Easy expansion

Quickly add seven USB 3.0 ports to any PC, allowing you to connect more peripherals with ease.

Fast Charge mode

One of the seven USB 3.0 ports supports Fast Charge mode.

Compact and portable

Fits easily into any bag for travel and can still function even without a power adapter.



DUB-1370

7-Port USB 3.0 Hub (One Port with Fast Charge Support)

Features

Connectivity

- Seven USB 3.0 ports
- Backwards compatible with USB 2.0 and USB 1.1

Fast Charge Mode

- One Fast Charge USB 3.0 port for mobile devices
- Does not require a PC to charge devices

Easy to Use

- Plug-and-play support
- Compact design
- Works on Windows, Mac, and Linux PCs

The D-Link DUB-1370 7-Port USB 3.0 Hub provides an easy way to add seven USB 3.0 ports to your notebook or desktop computer. One of the seven USB 3.0 ports supports Fast Charge mode, allowing you to reduce time for charging mobile devices. This means you can charge devices while also connect additional USB devices like digital and web cameras, card readers, hard drives, mice, keyboards, printers, scanners, and other peripherals.

Add Seven USB 3.0 Ports to Your Computer

With the DUB-1370 7-Port USB 3.0 Hub, you can conveniently add more USB 3.0 ports and connect up to seven USB peripheral devices. USB 3.0 technology supports data rates of up to 5 Gbps, which means that you can enjoy faster transfer speeds compared to previous USB standards.

Fast Charge Mode

One of the seven USB 3.0 ports supports Fast Charge mode. Battery Charging 1.2 compliance allows this port to supply charging current up to 1.5 A for chargeable devices.

Plug-and-play support

Simply connect the DUB-1370 to any PC (you can also plug in the power adapter if it is necessary). It's that easy - no drivers or software installation is required. Now you can connect up to seven additional USB devices to your laptop, notebook, or desktop computer.

7-Port USB 3.0 Hub (One Port with Fast Charge Support)

Technical Specifications	
Hardware	
Interfaces	<ul style="list-style-type: none"> • One USB 3.0 Type-A downstream port with Fast Charge mode support • Six USB 3.0 Type-A downstream ports • One USB 3.0 Type-A connector
LEDs	<ul style="list-style-type: none"> • Power LED
Network	
Standards	<ul style="list-style-type: none"> • USB 3.0 • USB 2.0 • USB 1.1 • OHCI • UHCI • EHCI • xHCI
Data rate	<ul style="list-style-type: none"> • Up to 5 Gbps
Connectivity rules	<ul style="list-style-type: none"> • Up to 127 devices • Up to five cascaded hubs
System requirements	<ul style="list-style-type: none"> • Available USB port (USB 3.0 is recommended) • Windows XP/Vista/7/8/10, Mac OS, Linux
Physical Parameters	
Dimensions (L x W x H)	<ul style="list-style-type: none"> • 168 x 35 x 13.5 mm
Environmental Conditions	
Power input	<ul style="list-style-type: none"> • From PC (USB bus powered) • 12 V / 2 A DC power adapter
Supplied charging current	<ul style="list-style-type: none"> • Max. 1.5 A for Battery Charging 1.2 compliant port (with power adapter) • 0.5 A for standard ports
Temperature	<ul style="list-style-type: none"> • Operating: 0 to 40 °C • Storage: -20 to 70 °C
Humidity	<ul style="list-style-type: none"> • Operating: 10% to 90% non-condensing • Storage: 5% to 90% non-condensing
Order Information	
Part Number	Description
DUB-1370	7-Port USB 3.0 Hub (One Port with Fast Charge Support)