SensoMAG RI

Conventional Fire Alarm Remote Indicator



- Big 360° visible LED indication
- Red LED color
- Up to 3 connected detectors

SensoMAG RI is a conventional fire alarm remote indicator designed for operation in fire alarm systems. Its main function is duplicating the light signaling of the activated automatic fire detector.

The remote indicator is suitable for application in conventional and addressable fire alarm systems and could serve for repeating the light indication of maximum 3 fire detectors connected to its input terminal. It is equipped with large, 360° visible, red LED indication. In activated state the LED lights on continuously.

Features

- Wall or Ceiling mounting
- IP 30 protection level
- Indoor use
- Red LED color

Technical Specifications

Operating Voltage Range	24VDC
Consumption in alarm state	7.5mA
Wire Gauge for terminals	0.5mm - 2.5mm
Operating temperature	-10°C to +60°C
Relative humidity resistance	(93 ± 3)% @ 40°C
Weight (including base)	~50g
Dimensions	86 x 86 x 32.5mm

Last update: 10/2026

info@teletek-electronics.bg
teletek-electronics.com